

DHI-ASL2101S DHI-ASL2101K

Bluetooth smart lock



Features

- 4-way opening: Bluetooth, Mifare Cards, passwords and mechanical keys
- Privacy password: xxx+password+xxx, preventing password to be seen by others
- Passage Mode and Non-disturbance Mode optional
- Auto lock when come across a consecutive invalid passwords or cards
- Low Voltage alarm(<4.5V)
- Huge storage: 50 cards, 50 passwords, 8 Bluetooth
- Emergency power supply outside
- Two colors optional
- Zinc alloy material

Technical Specification

Card

| | |
|------------------|---|
| Card Type | Mifare 1 |
| Card Features | Contactless, high security, all-in-one possible |
| Sensor Distance | < 20mm |
| Sensor Time | < 0.5s |
| Storage Capacity | 50 |

Password

| | |
|------------------|--------------------|
| Keyboard Type | All-touch keyboard |
| Password Length | 6-12 bits |
| Storage Capacity | 50 |

Battery

| | |
|------------------------|--------------------------------|
| Working Voltage | 6V, AA alkaline battery (4pcs) |
| Battery Life | About 1 year (10 units/D) |
| Low Battery Warning | < DC4.5V |
| Emergency Power Supply | 9V battery |

Structure

| | |
|----------------|------------------------|
| Door Thickness | 35-65mm (customizable) |
| Backset | 60/70mm |
| Material | Zinc alloy |

General

| | |
|---------------------|-----------------|
| Working Temperature | -20°C~+55°C |
| Relative Humidity | 10%~93% |
| Salt spray test | ≥200h |
| Lock case test | ≥100000 times |
| Package size | 315*230*160(mm) |
| Gross weight | 3.3Kg |
| Restore Default | Support |
| Reset | Support |
| Built-in Buzzer | Support |

DHI-ASL2101S DHI-ASL2101K

Selection

| | | | |
|---|----------------|--------|------------|
|  | DHI-ASL2101S-L | Silver | Left-open |
|  | DHI-ASL2101S-R | Silver | Right-open |
|  | DHI-ASL2101K-L | Black | Left-open |
|  | DHI-ASL2101K-R | Black | Right-open |

Dimensions

